


# Rotary Switch

## RCL 370 SERIES



適用於：

1. HI END 高級音響音量控制
2. PA大樓廣播系統
3. 資料切換開關
4. 多迴路、多接點(23段)各式信號切換

APPLICABLE TO :

1. Volume control of Hi-End audios.
2. Public audio system.
3. Data transfer switch, etc.
4. Signal Selection of multi-section (two wafers one section), multi-pole, multi-position (2-24 positions) electronic products.

### 特性規格 SPECIFICATION

項目 ITEM

定 格 RATING	DC 30V 0.5A
接觸電阻 CONTACT RESISTANCE	25m $\Omega$ MAX
絕緣電阻 INSULATION RESISTANCE	DC 500V 100M $\Omega$ MIN
耐 電 壓 WITHSTAND VOLTAGE	500V 1 MINUTE
動 作 力 TORQUE	1 TO 3 SECTION 2 $\pm$ 1kg OVER 3 SECTION 3 $\pm$ 1.5kg (REFERENCE)

### 適用迴路數及段數說明

#### ILLUSTRATION OF APPLICABLE POLE & POSITION

迴 路 POLE	段 數 POSITIONS	迴 路 POLE	段 數 POSITIONS
12	2	3	7~ 8
8	3	2	9~12
6	4	1	13~24
4	5~6		

